

JCM Tapped Outlet Repair Clamps - 103, 104, 173, 174, 133, 134, 123, 153, 163, 164

All Models of JCM Universal Clamp Couplings are available with tapped outlets for repair of direct tap pull outs and broken or split pipe requiring a service outlet.

HOW TO ORDER

<p>1. Select standard model, size and width clamp to fit pipe.</p> <p>2. Change model number to corresponding Tapped Outlet Clamp Model Number.</p>	<p>3. Select size and type of tapped outlet from outlet guide below. Note minimum widths and range/sizes.</p> <p>4. Add Outlet Tap Code to clamp number. Add-On outlet price to standard clamp list price.</p>	<p>Ordering Example:</p> <p>For standard clamp to fit 6" Cast Iron Pipe with 12" width, with 2" IP outlet, order:</p> <p style="text-align: center;">103-0690-12 x 14IP</p>
---	--	--

Standard Clamp Model	Becomes Tapped Outlet Clamp Model
<p>101 Universal Clamp Coupling - Standard Range</p> <p>102 Universal Clamp Coupling - Extended Range</p> <p>131 All Stainless Steel UCC - Std Range</p> <p>132 All Stainless Steel UCC - Extd Range</p> <p>121 Gas Repair Clamp</p> <p>151 Gas Repair Clamp</p> <p>161 All Stainless Steel Fabricated Lug Clamp</p> <p>162 All Stainless Steel Fabricated Lug Clamp - Ext Range</p> <p>171 UCC - Standard Range - Removeable Lug</p> <p>172 UCC - Extended Range - Removeable Lug</p>	<p>103 Tapped Universal Clamp Coupling - Standard Range</p> <p>104 Tapped Universal Clamp Coupling - Extended Range</p> <p>133 Tapped All Stainless Steel UCC - Std Range</p> <p>134 Tapped All Stainless Steel UCC - Extd Range</p> <p>123 Tapped Gas Service Clamp</p> <p>153 Tapped All Stainless Steel Gas Service Clamp</p> <p>163 All Stainless Steel Tapped Fabricated Lug Clamp</p> <p>164 All Stainless Steel Tapped Fabricated Lug Clamp - Ext Range</p> <p>173 Tapped UCC - Standard Range - Removeable Lug</p> <p>174 Tapped UCC - Standard Range - Removeable Lug</p>

CLAMP RANGE/SIZE (IN.)	MINIMUM CLAMP LENGTH (IN.)	TYPE OF THREAD	TAP SIZE	ADD OUTLET TAP CODE	
				IP ORDER TAP CODE	CC ORDER TAP CODE
2.38 - 4.80	6	IP or CC	3/4"	06	07
			1"	08	09
2.38 - 14.00	7-1/2	IP or CC	3/4"	06	07
			1"	08	09
4.50 - 14.00	12	IP or CC	1-1/4"	10	11
4.50 - 14.00	12	IP or CC	1-1/2"	12	13
4.50 - 14.00	12	IP	2"	14	-
4.50 - 14.00	12	CC	2"	-	15

JCM
103
123
173



JCM
133
153



JCM
163

